

## 300mA, Ultra-Low IQ, Low Dropout LDO

### 1 Features

- Input Voltage Range: 2.5V to 5.5V
- Output Current: 300mA
- Standard Fixed Output Voltage Options
  - 1.2V, 1.5V, 1.8V, 2.5V, 2.8V, 3.0V, 3.3V, 3.6V and 5.0V
- 0.5μA quiescent current at no load
- <0.3μA shutdown current
- ±2% output voltage accuracy
- Thermal shutdown protection
- Current limit protection
- RoHS Compliant and Halogen Free

### 2 Applications

- Portable Electric Devices
- Battery Powered Equipment
- Audio/Video Equipment

### 3 Description


The GD30LD2001 is a ultra-low quiescent low dropout linear regulator with 300mA driving current. With less than 0.5μA quiescent current at no load, is ideally suited for portable devices. The GD30LD2001 provides 1.2V to 5.0V output voltage for multiple application and it is with build-in thermal shutdown and current limit protection functions.

Device Information<sup>1</sup>

PART NUMBER	PACKAGE	BODY SIZE(NOM)
GD30LD2001	SOT23-3	2.92mm x 1.60mm
	SOT23-5	2.92mm x 1.60mm
	DFN1x1-4	1.00mm x 1.00mm

1. For all available packages, see the [Package Information](#) and [Ordering Information](#) at the end of data sheet.

### Simplified Application Schematic




## Table of Contents

<b>1</b>	<b>Features .....</b>	<b>1</b>
<b>2</b>	<b>Applications .....</b>	<b>1</b>
<b>3</b>	<b>Description .....</b>	<b>1</b>
	<b>Table of Contents .....</b>	<b>2</b>
<b>4</b>	<b>Device Overview .....</b>	<b>3</b>
4.1	Pinout and Pin Assignment .....	3
4.2	Pin Description .....	3
<b>5</b>	<b>Parameter Information .....</b>	<b>4</b>
5.1	Absolute Maximum Ratings .....	4
5.2	Recommended Operation Conditions .....	4
5.3	Electrical Sensitivity .....	4
5.4	Thermal Resistance .....	4
5.5	Electrical Characteristics .....	5
5.6	Typical Characteristics .....	6
<b>6</b>	<b>Functional Description .....</b>	<b>7</b>
6.1	Block Diagram .....	7
6.2	Operation .....	7
6.3	Device Mode Description .....	8
<b>7</b>	<b>Application Information .....</b>	<b>9</b>
7.1	Typical Application Circuit .....	9
7.2	Detailed Design Description .....	9
7.3	Power Dissipation .....	9
7.4	Typical Application Curves .....	11
<b>8</b>	<b>Layout Guidelines and Example .....</b>	<b>13</b>
<b>9</b>	<b>Package Information .....</b>	<b>14</b>
9.1	Outline Dimensions .....	14
9.2	Recommended Land Pattern .....	20
<b>10</b>	<b>Ordering Information .....</b>	<b>23</b>
<b>11</b>	<b>Revision History .....</b>	<b>24</b>

## 4 Device Overview

### 4.1 Pinout and Pin Assignment



### 4.2 Pin Description

NAME	PINS			PIN TYPE <sup>1</sup>	FUNCTION
	SOT23-3	SOT23-5	DFN1x1-4		
GND	1	2	2	G	Ground pin.
IN	3	1	4	P	Power supply input pin.
OUT	2	5	1	P	Output pin.
EN		3	3	I	Enable control pin. Active high.
NC		4			No connection.

1. I = Input, P = Power, G = Ground.

## 5 Parameter Information

### 5.1 Absolute Maximum Ratings

Exceeding the operating temperature range(unless otherwise noted)<sup>1</sup>

SYMBOL	PARAMETER	MIN	MAX	UNIT
V <sub>IN</sub>	IN	-0.3	6	V
V <sub>EN</sub>	EN	-0.3	6	V
V <sub>OUT</sub>	OUT	-0.3	6	V
	V <sub>OUT</sub> to V <sub>IN</sub>	-6	0.3	V
T <sub>J</sub>	Operating junction temperature	-40	150	°C
T <sub>stg</sub>	Storage temperature	-55	150	°C
PD	Power dissipation, SOT23-3 @ T <sub>A</sub> = 25°C		0.3	W
	Power dissipation, SOT23-5 @ T <sub>A</sub> = 25°C		0.4	
	Power dissipation, DFN1x1-4 @ T <sub>A</sub> = 25°C		0.4	

1. The maximum ratings are the limits to which the device can be subjected without permanently damaging the device. Note that the device is not guaranteed to operate properly at the maximum ratings. Exposure to the absolute maximum rating conditions for extended periods may affect device reliability.

### 5.2 Recommended Operation Conditions

SYMBOL <sup>1,2</sup>	PARAMETER	MIN	TYP	MAX	UNIT
V <sub>IN</sub>	Input supply voltage range	2.5		5.5	V
I <sub>OUT</sub>	Output current	0		300	mA
T <sub>J</sub>	Operating junction temperature <sup>2</sup>	-40		125	°C
T <sub>A</sub>	Operating ambient temperature <sup>2</sup>	-40		85	°C

1. The device is not guaranteed to function outside of its operating conditions.
2. In applications where high power dissipation and poor package thermal resistance is present, the maximum ambient temperature can need to be derated.

### 5.3 Electrical Sensitivity

SYMBOL	CONDITIONS	VALUE	UNIT
V <sub>ESD(HBM)</sub>	Human-body model (HBM), ANSI/ESDA/JEDEC JS-001-2017 <sup>1</sup>	±2000	V
V <sub>ESD(CDM)</sub>	Charge-device model (CDM), ANSI/ESDA/JEDEC JS-002-2022 <sup>2</sup>	±200	V

1. JEDEC document JEP155 states that 500-V HBM allows safe manufacturing with a standard ESD control process.
2. JEDEC document JEP157 states that 250-V CDM allows safe manufacturing with a standard ESD control process.

### 5.4 Thermal Resistance

SYMBOL <sup>1</sup>	CONDITIONS	PACKAGE	VALUE	UNIT
Θ <sub>JA</sub>	Natural convection, 2S2P PCB	SOT23-3	330	°C/W
		SOT23-5	250	°C/W

## Thermal Resistance(Continued)

SYMBOL <sup>1</sup>	CONDITIONS	PACKAGE	VALUE	UNIT
$\Theta_{JA}$	Natural convection, 2S2P PCB	DFN1x1-4	250	°C/W

1. Thermal characteristics are based on simulation, and meet JEDEC document JESD51-7.

## 5.5 Electrical Characteristics

$V_{IN} = V_{EN} = 5V$ ,  $C_{IN} = C_{OUT} = 1\mu F$ ,  $T_A = 25^\circ C$ , unless otherwise noted.

SYMBOL	PARAMETER	CONDITIONS	MIN	TYP	MAX	UNIT
$V_{IN}$	Operating input voltage		2.5		5.5	V
$V_{OUT}$	Output voltage accuracy	$V_{IN} = V_{OUT} + 1V$ , $I_{OUT} = 1mA$	-2		+2	%
$I_{OUT}$	Output current		300			mA
$I_Q$	Quiescent current	$V_{IN} = V_{EN}$ , no load		0.3	0.5	$\mu A$
$I_{SHDN}$	Shutdown current	$V_{EN} = 0V$			0.3	$\mu A$
$V_{DO}$	Dropout voltage <sup>2</sup>	$V_{OUT} = 3.3V$ , $I_{OUT} = 300mA$		400		mV
		$V_{OUT} = 1.8V$ , $I_{OUT} = 300mA$		700		
$\Delta_{LINE}$	Line regulation	$V_{OUT} + 1 \leq V_{IN} \leq 5.5V$ , $I_{OUT} = 1mA$		5		mV
$\Delta_{LOAD}$	Load regulation	$1mA \leq I_{OUT} \leq 300mA$		20		mV
$V_{EN\_RISE}$	Rising enable threshold	EN input voltage high	0.6			V
$V_{EN\_FALL}$	Falling enable threshold	EN input voltage low			0.2	V
PSRR	Power supply rejection ration	$V_{IN} = V_{OUT} + 1V$ , $I_{OUT} = 10mA$ , $f = 1KHz$		60		dB
$T_{TSD}$	Thermal shutdown temperature <sup>1</sup>			150		°C
$T_{HYS}$	Thermal shutdown hysteresis <sup>1</sup>			20		°C

1. Guaranteed by design and engineering sample characterization.

2. The dropout voltage is defined as  $V_{IN} - V_{OUT}$ , when  $V_{OUT}$  is 90% of the value of  $V_{OUT}$ .

## 5.6 Typical Characteristics

$C_{IN} = C_{OUT} = 1.0\mu F$ ,  $T_A = 25^\circ C$ , unless otherwise noted.




Figure 1. Shutdown Current vs. Output Current




Figure 2. Quiescent Current vs. Temperature




Figure 3. Dropout Voltage vs. Output Current




Figure 4. Output Voltage vs. Output Current

## 6 Functional Description

### 6.1 Block Diagram




Figure 5. GD30LD2001 Functional Block Diagram

### 6.2 Operation

The external input and output capacitors of GD30LD2001 series must be properly selected for stability and performance. Use a 1 $\mu$ F or larger input capacitor and place it close to the device IN and GND pins. The GD30LD2001 series is designed specifically to work with low ESR ceramic output capacitor in space-saving and performance consideration. Place the output capacitor close to the device OUT and GND pins. Increasing capacitance and decreasing ESR can improve the circuit's PSRR and line transient response.

#### 6.2.1 Dropout Voltage

The GD30LD2001 series use a PMOS pass transistor to achieve low dropout. When  $(V_{IN} - V_{OUT})$  is less than the dropout voltage ( $V_{DO}$ ), the PMOS pass device is in the linear region of operation and the input-to-output resistance is the  $R_{DS(ON)}$  of the PMOS pass element.  $V_{DO}$  scales approximately with the output current because the PMOS device behaves as a resistor in dropout condition.

As any linear regulator, PSRR and transient response are degraded as  $(V_{IN} - V_{OUT})$  approaches dropout condition.

#### 6.2.2 Current Limit Protection

The GD30LD2001 series contain the current limiter of output power transistor, which monitors and controls the transistor, limiting the output current to 560mA (typical). The output can be shorted to ground indefinitely without damaging the part.

### **6.2.3 Thermal Shutdown**

The over temperature protection function of GD30LD2001 series will turn off the P-MOSFET when the junction temperature exceeds 150°C (typical). Once the junction temperature cools down by approximately 20°C, the regulator will automatically resume operation.

## **6.3 Device Mode Description**

### **6.3.1 Device Enable**

The GD30LD2001 series has an EN pin to turn on or turn off the regulator. When the EN pin is in logic high, the regulator will be turned on. When the EN pin is in logic low, the shutdown current is almost 0.3μA typical. The EN pin may be directly tied to IN to keep the part on.

## 7 Application Information

The GD30LD2001 is high voltage, low power consumption and low dropout LDO. Its output voltage is fixed, providing two versions with or without enable.

### 7.1 Typical Application Circuit




Figure 6. Reference Design Schematic

### 7.2 Detailed Design Description

#### 7.2.1 Input Capacitor Selection

A 1µF or larger ceramic capacitor is recommended to connect between IN and GND pins to decouple input power supply glitch and noise. The amount of the capacitance may be increased without limit. This input capacitor must be located as close as possible to the device to assure input stability and less noise. For PCB layout, a wide copper trace is required for both IN and GND.

#### 7.2.2 Output Capacitor Selection

Any output capacitor meeting the minimum 1mΩ ESR (Equivalent Series Resistance) and effective capacitance between 1µF and 22µF requirement may be used and temperature characteristics are X7R or X5R. Higher capacitance values help to improve load/line transient response. The output capacitance may be increased to keep low undershoot/overshoot. Place output capacitor as close as possible to OUT and GND pins. Increasing capacitance and decreasing ESR can also improve the circuit's PSRR and line transient response.

### 7.3 Power Dissipation

Circuit reliability demands that proper consideration is given to device power dissipation, location of the circuit on the printed circuit board (PCB), and correct sizing of the thermal plane. The PCB area around the regulator must be as free as possible of other heat-generating devices that cause added thermal stresses.

Power dissipation in the regulator depends on the input-to-output voltage difference and load conditions.

$$P_D = (V_{IN} - V_{OUT}) \times I_{OUT} + V_{IN} \times I_{GND} \quad (1)$$

$V_{IN} \times V_{OUT}$  represents the static power consumption of the LDO, the value is relatively small and can be ignored. An important note is that power dissipation can be minimized, and thus greater efficiency achieved, by proper selection of the system voltage rails. Proper selection allows the minimum input-to-output voltage differential to be obtained. The low dropout of the device allows for maximum efficiency across a wide range of output voltages.

The main heat conduction path for the device is through the thermal pad on the package. As such, the thermal pad must be soldered to a copper pad area under the device. This pad area contains an array of plated vias that conduct heat to any inner plane areas or to a bottom-side copper plane.

The maximum power dissipation determines the maximum allowable junction temperature ( $T_J$ ) for the device. Power dissipation and junction temperature are most often related by the junction-to-ambient thermal resistance ( $\theta_{JA}$ ) of the combined PCB, device package, and the temperature of the ambient air ( $T_A$ ). The maximum power dissipation can be calculated as below:

$$T_J = T_A + \theta_{JA} \times P_D \quad (2)$$

$$I_{OUT} = \frac{T_J - T_A}{\theta_{JA} \times (V_{IN} - V_{OUT})} \quad (3)$$

## 7.4 Typical Application Curves

$V_{IN} = 5V$ ,  $V_{OUT} = 3.3V$ ,  $C_{IN} = C_{OUT} = 1\mu F$ ,  $T_A = 25^\circ C$ , unless otherwise noted.




Figure 7. VIN Startup without Load




Figure 8. VIN Shutdown without Load




Figure 9. VIN Startup with Load




Figure 10. VIN Shutdown with Load




Figure 11. EN Startup with Load





Figure 12. EN Shutdown with Load

## Typical Application Curves(Continued)

$V_{IN} = 5V$ ,  $V_{OUT} = 3.3V$ ,  $C_{IN} = C_{OUT} = 1\mu F$ ,  $T_A = 25^\circ C$ , unless otherwise noted.



## 8 Layout Guidelines and Example


By placing input and output capacitors on the same side of the PCB as the LDO, and placing them as close as is practical to the package can achieve the best performance. The ground connections for input and output capacitors must be back to the GD30LD2001 ground pin using as wide and as short of a copper trace as is practical.

Connections using long trace lengths, narrow trace widths, and/or connections through via must be avoided. These add parasitic inductances and resistance that results in worse performance especially during transient conditions.

## 9 Package Information

### 9.1 Outline Dimensions

#### SOT23-3 Package Outline




#### NOTES:

1. All dimensions are in millimeters.
2. Package dimensions does not include mold flash, protrusions, or gate burrs.
3. Refer to the [Table 1 SOT23-3 dimensions\(mm\)](#).


Table 1. SOT23-3 dimensions(mm)

SYMBOL	MIN	TYP	MAX
A	1.05		1.25
A1	0.00		0.10
A2	1.05	1.10	1.15
b	0.30		0.40
c	0.10		0.20
D	2.82	2.92	3.02
E	2.65		2.95
E1	1.50	1.60	1.70
e	0.95 BSC		
e1	1.90 BSC		
L	0.30		0.60
L1	0.6 REF		
θ	0°		8°


## SOT23-5 Package Outline



TOP VIEW



SIDE VIEW



FRONT VIEW


NOTES: (continued)

1. Refer to the [Table 2 SOT23-5 dimensions\(mm\)](#).


Table 2. SOT23-5 dimensions(mm)

SYMBOL	MIN	TYP	MAX
A	1.05		1.25
A1	0.00		0.10
A2	1.05	1.10	1.15
b	0.30		0.50
c	0.10		0.20
D	2.82	2.92	3.02
E	2.65		2.95
E1	1.50	1.60	1.70
e	0.95 BSC		
e1	1.90 BSC		
L	0.30		0.60
L1	0.60 REF		
θ	0°		8°


## DFN1x1-4 Package Outline



TOP VIEW



BOTTOM VIEW



FRONT VIEW

NOTES: (continued)


1. Refer to the [Table 3 DFN1x1-4 dimensions\(mm\)](#).

Table 3. DFN1x1-4 dimensions(mm)

SYMBOL	MIN	TYP	MAX
A	0.35		0.40
A1	0.00	0.02	0.05
A2	0.127REF		
b	0.15	0.20	0.25
D	0.95	1.00	1.05
D2	0.38	0.48	0.58
D3	0.230	0.330	0.430
E	0.95	1.00	1.05
e	0.65BSC		
E2	0.38	0.48	0.58
E3	0.230	0.330	0.430
L	0.20	0.25	0.30
L2	0.103REF		
L3	0.075REF		
L4	0.208REF		
L5	0.200 REF		

## 9.2 Recommended Land Pattern


### SOT23-3 Land Pattern Example



#### NOTES:

1. Refer to the IPC-7351 can also help you complete the designs.
2. Exposed metal shown.
3. Drawing is 20X scale.


## SOT23-5 Land Pattern Example



### NOTES: (continued)

1. Refer to the IPC-7351 can also help you complete the designs.
2. Exposed metal shown.
3. Drawing is 20X scale.

## DFN1x1-4 Land Pattern Example



### NOTES: (continued)

1. Refer to the IPC-7351 can also help you complete the designs.
2. Exposed metal shown.
3. Drawing is 20X scale.

## 10 Ordering Information

Ordering Code	Package Type	ECO Plan	Packing Type	MOQ	OP Temp(°C)
GD30LD2001BSTR-I12	SOT23-3	Green	Tape & Reel	3000	-40°C to +125°C
GD30LD2001BSTR-I15	SOT23-3	Green	Tape & Reel	3000	-40°C to +125°C
GD30LD2001BSTR-I18	SOT23-3	Green	Tape & Reel	3000	-40°C to +125°C
GD30LD2001BSTR-I25	SOT23-3	Green	Tape & Reel	3000	-40°C to +125°C
GD30LD2001BSTR-I28	SOT23-3	Green	Tape & Reel	3000	-40°C to +125°C
GD30LD2001BSTR-I30	SOT23-3	Green	Tape & Reel	3000	-40°C to +125°C
GD30LD2001BSTR-I33	SOT23-3	Green	Tape & Reel	3000	-40°C to +125°C
GD30LD2001BSTR-I36	SOT23-3	Green	Tape & Reel	3000	-40°C to +125°C
GD30LD2001BSTR-I50	SOT23-3	Green	Tape & Reel	3000	-40°C to +125°C
GD30LD2001NSTR-I12	SOT23-5	Green	Tape & Reel	3000	-40°C to +125°C
GD30LD2001NSTR-I15	SOT23-5	Green	Tape & Reel	3000	-40°C to +125°C
GD30LD2001NSTR-I18	SOT23-5	Green	Tape & Reel	3000	-40°C to +125°C
GD30LD2001NSTR-I25	SOT23-5	Green	Tape & Reel	3000	-40°C to +125°C
GD30LD2001NSTR-I28	SOT23-5	Green	Tape & Reel	3000	-40°C to +125°C
GD30LD2001NSTR-I30	SOT23-5	Green	Tape & Reel	3000	-40°C to +125°C
GD30LD2001NSTR-I33	SOT23-5	Green	Tape & Reel	3000	-40°C to +125°C
GD30LD2001NSTR-I36	SOT23-5	Green	Tape & Reel	3000	-40°C to +125°C
GD30LD2001NSTR-I50	SOT23-5	Green	Tape & Reel	3000	-40°C to +125°C
GD30LD2001JETR-I12	DFN1x1-4	Green	Tape & Reel	10000	-40°C to +125°C
GD30LD2001JETR-I15	DFN1x1-4	Green	Tape & Reel	10000	-40°C to +125°C
GD30LD2001JETR-I18	DFN1x1-4	Green	Tape & Reel	10000	-40°C to +125°C
GD30LD2001JETR-I25	DFN1x1-4	Green	Tape & Reel	10000	-40°C to +125°C
GD30LD2001JETR-I28	DFN1x1-4	Green	Tape & Reel	10000	-40°C to +125°C
GD30LD2001JETR-I30	DFN1x1-4	Green	Tape & Reel	10000	-40°C to +125°C
GD30LD2001JETR-I33	DFN1x1-4	Green	Tape & Reel	10000	-40°C to +125°C
GD30LD2001JETR-I36	DFN1x1-4	Green	Tape & Reel	10000	-40°C to +125°C
GD30LD2001JETR-I50	DFN1x1-4	Green	Tape & Reel	10000	-40°C to +125°C

## 11 Revision History

REVISION NUMBER	DESCRIPTION	DATE
1.0	Initial release and device details	2024

## Important Notice

This document is the property of GigaDevice Semiconductor Inc. and its subsidiaries (the "Company"). This document, including any product of the Company described in this document (the "Product"), is owned by the Company according to the laws of the People's Republic of China and other applicable laws. The Company reserves all rights under such laws and no Intellectual Property Rights are transferred (either wholly or partially) or licensed by the Company (either expressly or impliedly) herein. The names and brands of third party referred thereto (if any) are the property of their respective owner and referred to for identification purposes only.

The Company makes no representations or warranties of any kind, express or implied, with regard to the merchantability and the fitness for a particular purpose of the Product, nor does the Company assume any liability arising out of the application or use of any Product described in this document. Any information provided in this document is provided only for reference purposes. It is the sole responsibility of the user of this document to determine whether the Product is suitable and fit for its applications and products planned, and properly design, program, and test the functionality and safety of its applications and products planned using the Product. Unless otherwise expressly specified in the datasheet of the Product, the Product is designed, developed, and/or manufactured for ordinary business, industrial, personal, and/or household applications only, and the Product is not designed or intended for use in (i) safety critical applications such as weapons systems, nuclear facilities, atomic energy controller, combustion controller, aeronautic or aerospace applications, traffic signal instruments, pollution control or hazardous substance management; (ii) life-support systems, other medical equipment or systems (including life support equipment and surgical implants); (iii) automotive applications or environments, including but not limited to applications for active and passive safety of automobiles (regardless of front market or aftermarket), for example, EPS, braking, ADAS (camera/fusion), EMS, TCU, BMS, BSG, TPMS, Airbag, Suspension, DMS, ICMS, Domain, ESC, DCDC, e-clutch, advanced-lighting, etc.. Automobile herein means a vehicle propelled by a self-contained motor, engine or the like, such as, without limitation, cars, trucks, motorcycles, electric cars, and other transportation devices; and/or (iv) other uses where the failure of the device or the Product can reasonably be expected to result in personal injury, death, or severe property or environmental damage (collectively "Unintended Uses"). Customers shall take any and all actions to ensure the Product meets the applicable laws and regulations. The Company is not liable for, in whole or in part, and customers shall hereby release the Company as well as its suppliers and/or distributors from, any claim, damage, or other liability arising from or related to all Unintended Uses of the Product. Customers shall indemnify and hold the Company, and its officers, employees, subsidiaries, affiliates as well as its suppliers and/or distributors harmless from and against all claims, costs, damages, and other liabilities, including claims for personal injury or death, arising from or related to any Unintended Uses of the Product.

Information in this document is provided solely in connection with the Product. The Company reserves the right to make changes, corrections, modifications or improvements to this document and the Product described herein at any time without notice. The Company shall have no responsibility whatsoever for conflicts or incompatibilities arising from future changes to them. Information in this document supersedes and replaces information previously supplied in any prior versions of this document.

© 2024 GigaDevice – All rights reserved